

VIDEO DOOR ENTRY SYSTEMS & KITS POWER SUPPLIES AND ACCESSORIES 

1205/B



The transformer has 2 outputs: one to supply the external unit and the electric lock, and one to supply the monitor. 500mA delayed protection fuse. Terminal board: AC230V input mains voltage $\sim\sim$ AC output for external unit and electric lock+ - 20V DC output for the monitor power supply. Dimensions: 105x85x85mm

VIDEO DOOR ENTRY SYSTEMS & KITS POWER SUPPLIES AND ACCESSORIES



1205/B

POWERCOM KIT SYSTEM POWER SUPPLY

MAIN FEATURES	
Alternating input voltage (VAC):	230
Alternating output voltage (VAC):	12
Output voltage (VDC):	20
Input connector:	Terminal block
Applicable to DIN rail:	Yes

GENERAL DATA	
Product height (mm):	85
Product width (mm):	105
Product depth (mm):	85
Type of finish:	Plastic
Product colour:	White
Operating temperature (°C):	5 ÷ 40